



**WARNING**  
ELECTRICAL SHOCK HAZARD

**READ and UNDERSTAND** these instructions before installing luminaire.

Disconnect the Electrical supply power at the services panel (fuse or circuit breaker box). Failure to do so could result in serious injury.

Only qualified electricians should install this luminaire and the installation **MUST** conform to the Canadian Electrical Code Part I and any local codes and ordinances. Make sure you have the proper tools and materials to complete the installation before attempting to install the luminaire.

## INSTALLATION

### MOUNTING USING 3/4" PLUG IN THE BACK

1. Do not touch the yellow portion of the LED array. Damage may occur.
2. Remove the four screws attaching the lens diffuser to the fixture.
3. Remove the screws attaching the housing cover to the housing.
4. Remove 3/4" plug from back for wiring access.
5. Fixture is best mounted by drilling through back of fixture securing it to the mounting surface using the appropriate mounting hardware for the surface. All unused holes must be plugged. Waterproof silicone will ensure a tight seal.
6. Fixture can also be pendant mounted by threading the customer supplied pendant through the 3/4" mounting hole on the top of the fixture.
7. Route the incoming power and ground leads through the hole located in the center of the back of the fixture and through the opening on the side of the LED array mounting post.
8. Complete the wiring to the incoming power and ground.
  - a. Connect the black fixture lead to the voltage supply lead.
  - b. Connect the white fixture lead to the neutral supply lead.
  - c. Connect the supply ground lead to the fixture ground screw (GREEN).
9. Replace the housing cover and lens diffuser.

### MOUNTING USING 1/2" PLUGS IN THE SIDE

1. Do not touch the yellow portion of the LED array. Damage may occur.
2. Remove the four screws attaching the lens diffuser to the fixture.
3. Remove the screws attaching the housing cover to the housing.
4. Remove 1/2" plug from direction you intend to feed conduit.
5. Fixture is best mounted by drilling through back of fixture securing it to the mounting surface using the appropriate mounting hardware for the surface. All unused holes must be plugged. Waterproof silicone will ensure a tight seal.
6. Complete the wiring to the incoming power and ground.
  - a. Connect the black fixture lead to the voltage supply lead.
  - b. Connect the white fixture lead to the neutral supply lead.
  - c. Connect the supply ground lead to the fixture ground screw (GREEN).
7. Replace the housing cover and lens diffuser.