

May 28, 2016

CER4742BWH30 120 V Triac or phase-cut dimmers

Brand	Type	Series	Model #	Wiring	watts	dimming method	Version Code	Max # of Luminaires	Notes	Min # of Luminaires for proper dimming	dimming range	
Lutron	C.L	Ariadni/Toggler C.L	AYCL-153P	Single-pole/3-way	150	Toggler	T8, T9	16	3-Way only works with a 3-Way switch	1	10-100%	
			TGCL-153P									
			Diva C.L									DVCL-153P
			Skylark C.L									SCL-153P
			Skylark Contour C.L									CTCL-153P
		Lumea C.L	LGCL-153P									
		Maestro C.L	MACL-153M	Single-pole/3-way/ multi-location	150	Digital	2014	16	3-Way only works with a 3-Way switch or dimmer companion MA-R (not a dimmer). Multi-location only work with MA-R	1		
			MSCL-VP153M	Single-pole/3-way/ multi-location	150	Digital/Vacancy Sensor	T2	16	3-Way only works with a 3-Way switch or dimmer companion MA-R (not a dimmer). Multi-location only work with MA-R	1		
						Digital/Occupancy Sensor						
			MRF2-6CL	Single-pole/3-way/ multi-location	150	Digital and Wireless	M6	16	3-Way or multi-location only works with companion MA-R (not a dimmer)	1		
	Nova T	NTCL-250	Single-pole	250	slide to off	BR Y02	27		1			
Grafik T	GT-150	Single-pole/3-way/ multi-location	150	Digital	T6	16	3-Way or multi-location only works with companion GT-AD (not a dimmer)	1				
RF C.L	Grafik T RF				GTJ 150							
Wireless	Caseta	PD-6WCL	Single-pole or multi-location	150	Digital and Wireless	SD11	16	Multi-location only works with Pico wireless remote PJ2	1			
Leviton	Universal Dimmer	Decora	DSL06-1L	Single-pole/3-Way	300	slide with ON/OFF button	NA	33	3-Way only works with a 3-Way switch	1		
		Illuma Tech	IPL06-10	Single-pole/3-Way	150	slide with ON/OFF button	NA	16	3-Way only works with a 3-Way switch	1		
		Sureslide	6672-1L	single	150	slide to off	NA	16		1		
		Sureslide	6674-P0	Single-pole/3-Way	150	slide with ON/OFF button	NA	16	3-Way only works with a 3-Way switch	1		
		Renu	REL06	Single-pole/3-Way	300	Digital	NA	33	3-Way only works with remote RE00R Requires neutral wire connection	1		
		Decora Digital	DDMX1-BL	Single-pole/3-Way	450	Digital or Bluetooth	NA	50	3-Way only works with remote DDOOR-DL Requires neutral wire connection	1		

