

EVT1030D3 120 V Triac/Phase-cut dimmers											
Brand	Type	Series	Model #	Wiring	watts	dimming method	Version Code	Max # of Luminaires	Notes	Min # of Luminaires for proper dimming	minimum dimming range
Lutron	C.L	Ariadni/Toggler C.L	AYCL-153P	Single-pole/3-way	150	Toggler	T8, T9	21	3-Way only works with a 3-Way switch	1	3%
			TGCL-153P								
		Diva C.L	DVCL-153P								
		Skylark C.L	SCL-153P								
		Skylark Contour C.L	CTCL-153P								
	Lumea C.L	LGCL-153P									
	C.L	Maestro C.L	MACL-153M	Single-pole/3-way/multi-location	150	Digital	2014	21	3-Way only works with a 3-Way switch or dimmer companion MA-R (not a dimmer). Multi-location only work with MA-R	1	12%
			MSCV-VP153M	Single-pole/3-way/multi-location	150	Digital/Vacancy Sensor	T2	21	3-Way only works with a 3-Way switch or dimmer companion MA-R (not a dimmer). Multi-location only work with MA-R	1	12%
			MSCV-OP153M	Single-pole/3-way/multi-location	150	Digital/Occupancy Sensor					
			MRF2-6CL	Single-pole/3-way/multi-location	150	Digital and Wireless	M6	21	3-Way or multi-location only works with companion MA-R (not a dimmer)	1	12%
Nova T		NTCL-250	Single-pole	250	slide to off	BR Y02	35		1	11%	
RF C.L	Grafik T RF	GTJ 150	Single-pole/3-way/multi-location	150	Digital		21	3-Way or multi-location only works with companion GT-AD (not a dimmer)	1	10%	
Wireless	Caseta	PD-6WCL	Single-pole or multi-location	150	Digital and Wireless	SD11	21	Multi-location only works with Pico wireless remote PJ2	1	0%	
Leviton	Universal Dimmer	Decora	DSL06-1L	Single-pole/3-Way	300	slide with ON/OFF button	NA	42	3-Way only works with a 3-Way switch	1	37%
		Illuma Tech	IPL06-10	Single-pole/3-Way	150	slide with ON/OFF button	NA	21	3-Way only works with a 3-Way switch	1	11%
		Sureslide	6672-1L	single	150	slide to off	NA	21		1	23%
		Sureslide	6674-P0	Single-pole/3-Way	150	slide with ON/OFF button	NA	21	3-Way only works with a 3-Way switch	1	12%
		Renu	REL06	Single-pole/3-Way	300	Digital	NA	42	3-Way only works with remote RE00R Requires neutral wire connection	1	23%
		Decora Digital	DDMX1-BL	Single-pole/3-Way	450	Digital or Bluetooth	NA	63	3-Way only works with remote DDOOR-DL Requires neutral wire connection	1	15%

