

| 120 V Triac or phase-cut dimmers | | | | | | | | |
|----------------------------------|------------------|---------------------|--------------|--------|--------------|---------------------|--|---------------|
| Brand | Type | Series | Model # | Wiring | Version Code | Max # of Luminaires | Min # of Luminaires for proper dimming | dimming range |
| Lutron | C.L | Ariadni/Toggler C.L | AYCL-153P | 3-Way | T4, T8 | 5 | 1 | 2% - 100% |
| | | | TGCL-153P | | | | | |
| | | Diva C.L | DVCL-153P | | | | | |
| | | Skylark C.L | SCL-153P | | | | | |
| | | Skylark Contour C.L | CTCL-153P | | | | | |
| | | Lumea C.L | LGCL-153P | | | | | |
| | Maestro C.L | MACL-153M | 3-Way | 2014 | 5 | 1 | 10% - 100% | |
| | | MSCL-VP153M | single/multi | T2 | 5 | 1 | 10% - 100% | |
| | | MSCL-OP153M | single/multi | | | | | |
| | | MRF2-6CL | NA | M6 | 5 | 1 | 10% - 100% | |
| Grafik T | GT-150 | single | T6 | 5 | 1 | 9% - 100% | | |
| RF C.L | Grafik T RF | GTJ 150 | single | M6 | 5 | 1 | 9% - 100% | |
| Wireless | Caseta | PD-6WCL | NA | SD11 | 5 | 1 | 1% - 100% | |
| Leviton | Universal Dimmer | Decora | DSL06-1L | 3-Way | NA | 11 | 1 | 40% - 100% |
| | | Illuma Tech | IPL06-10 | 3-Way | NA | 5 | 1 | 12% - 100% |
| | | Sureslide | 6672-1L | single | NA | 5 | 1 | 26% - 100% |
| | | Sureslide | 6674-P0 | 3-Way | NA | 5 | 1 | 13% - 100% |

